

Users

From the users form the user management can be done.

User Administration ✕

Users

Groups

Filter
 All
 Local
 External

User id	Group	Name	Type
oper	operators	Operator	local
rlam	NetYCE	Ronny Lam	local
rmutsaers	NetYCE	Ramon Mutsaers	local
rpost	appmgmt	Rolf Post	local
wgerrits	NetYCE	Wim Gerrits	local
xml	NetYCE	Functional user – Yce exchange api	local
yspeerte	NetYCE	NetYCE support	local

+ 🗑 🔗

UserID

Full name

Group id

Permission levels

Global level

Client type	Description	Level
A	UCL	Manager
C	Cable Service Provider	Manager
FUJ	FUJITSU	Manager

User_type

Last login

User email

User tel User mobile

Notes

Password Expire Force Max age

Verification Set password Current age

Apply


Close

Technical documentation - <https://wiki.netyce.com/>

Add user

To add a user, just click the + and enter the user id. The user id can be changed at a later time when needed.

Delete user

By selecting the user and clicking the  button. Confirmation will be asked before a user is actually deleted.

Find user

It's possible to search for a user by using the  button and entering the user id. It isn't possible to search for a user by name.

Manage user

When selecting a user, the details of that user will be displayed. These variables can be set and stored by using the **[Apply]** button.

Permission levels

The permission settings will be updated as soon as the [group](#) id is set.

Password management

The password can be set by entering the password and clicking the **[Set password]** button. The new password can also be expired by using the *Expire* checkbox.

The maximum age of the password can be set in the Max age field. This value is in days. A value of 0, sets no limit.

From:
<https://wiki.netyce.com/> - **Technical documentation**

Permanent link:
https://wiki.netyce.com/doku.php?id=menu:admin:users:user_admin

Last update: **2024/07/03 12:31**

